

TITLE OF THE INVENTION

EXTENDED KEY GENERATOR, ENCRYPTION/DECRYPTION UNIT,
EXTENDED KEY GENERATION METHOD, AND STORAGE MEDIUM
CROSS-REFERENCE TO RELATED APPLICATIONS

5 This application is based upon and claims the
benefit of priority from the prior Japanese Patent
Application No. 11-244176, filed August 31, 1999, the
entire contents of which are incorporated herein by
reference.

10 BACKGROUND OF THE INVENTION

 The present invention relates to an extended key
generator, encryption/decryption unit, and storage
medium, which are applied to secret key block cipher.

 In the fields of recent computer and communication
15 technologies, a cryptography technology for
transmitting encrypted transmission data, and restoring
the received contents by decrypting received data is
prevalent. In such cipher technology, a cryptography
algorithm that uses a secret key (to be referred to as
20 a common key hereinafter) in both encryption and
decryption is called common key cipher. In common key
cipher, an input message is segmented into input blocks
each having a fixed length, and the segmented blocks
undergo randomization based on a key to generate
25 ciphertext. As such common key cipher, a scheme
called, e.g., DES (data encryption standard) is
prevalently used.

09652157.083100

In encryption based on DES, as shown in FIG. 1A, data obtained via initial permutation IP of plaintext undergoes 16 processes using round functions. Furthermore, the data that has undergone 16 rounds undergoes inverse permutation IP^{-1} of the initial permutation, thus obtaining ciphertext. On the other hand, by giving an extended key generated from the original key to each round function, a process in that round function is executed.

That is, an encryption apparatus based on DES has as principal building components a data randomization part for randomizing data to be encrypted using a large number of round functions, and a key generator for giving an extended key to each round function of the data randomization part. Note that the conventional key generator generates a key by rearranging bits using a table or wiring lines, using the same key as that of a data encryption unit, or randomly extracting from key bits.

In decryption based on DES, as shown in FIG. 1B, data to be decrypted undergoes 16 rounds in an order inverse to that upon encryption. Hence, a key generator generates extended keys in order from a key used in the last round function upon encryption.

The first merit in DES lies in the arrangement of encryption and decryption circuits; they can commonize most components. That is, as shown in FIGS. 1A and 1B,

09652157.083100

an identical circuit is used for the round functions of the data randomization part, although the input order of extended key is reversed upon encryption and decryption.

5 The second merit of DES is a small number of keys to be managed, since encryption and decryption are done using a single common key. In DES, in order to generate extended keys in normal and reverse orders on the basis of a sole common key, the key generator
10 executes the following processes.

 That is, a common key undergoes left rotate-shift (left rotation) to generate each extended key. Note that the total value of rotation amounts is defined to match the number of bits of the common key, and an
15 intermediate key is finally returned to an initial state (common key). In this manner, the last extended key upon encryption can be generated to have the same value as that of the first extended key upon decryption. Upon decryption, a common key undergoes
20 right rotate-shift (right rotation) to generate extended key in reverse order.

 However, since the processes of the key generator are implemented by only permutation processes in DES, key generally called weak keys which have low security
25 are present. Note that the weak keys mean extended keys which have identical values, and include a case wherein all extended keys K1 to K16 are equal to each

001280" 25725960

other ($K_1 = K_2 = \dots K_{16}$), and a case wherein half extended keys K_1 to K_8 and K_9 to K_{16} are equal to each other ($K_1 = K_{16}, K_2 = K_{15}, \dots, K_8 = K_9$).

However, generation of such weak keys is not
5 a menace but can be sufficiently prevented by adding
a device for removing input of a common key having
a pattern for generating weak keys to an extended key
generator, or adding to a cipher generation apparatus
a device for determining whether or not generated
10 extended keys are weak keys, and removing them if they
are weak keys.

However, when such device that prevents generation
of weak keys is added, the prices of the extended key
generator and encryption/decryption unit rise, and also
15 their circuit scales increase.

In addition to DES, a cryptosystem that can offer
cryptological robustness upon using different extended
keys in units of round functions by preventing
generation of weak keys, and can improve the
20 cryptological robustness has been demanded.

As described above, in the conventional extended
key generator and encryption/decryption unit, when
a device that prevents generation of weak keys is
added to avoid low security, the prices of the extended
25 key generator and encryption/decryption unit rise, and
also their circuit scales increase.

Even when generation of weak keys is prevented,

09652157-083100

processes in the key generator does not so contribute to improvement in cryptological robustness, and improvement in cryptological robustness is demanded.

BRIEF SUMMARY OF THE INVENTION

5 The present invention has been made in consideration of the above situation, and has as its object to provide an extended key generator, encryption/decryption unit, extended key generation method, and storage medium, which can improve
10 randomness of extended keys while suppressing an increase in apparatus price and circuit scale and preventing generation of weak keys, and can improve cryptological robustness.

 According to the first aspect of the present
15 invention, there is provided an extended key generator which has a plurality of cascade-connected key transform function sections for receiving different keys in units of rounds, and generating extended keys on the basis of the input keys, wherein each key
20 transform function section comprises first key transform means for executing a transform process using a predetermined substitution table on the basis of a first key obtained from the input key, and extended key computation means for computing the extended key on
25 the basis of a transformed result of the first key transform means, and a second key obtained from the input key.

09652157 "033100

According to another aspect of the present invention, there is provided an encryption/decryption unit which comprises an extended key generator, comprising a data randomization part for encrypting
5 input plaintext on the basis of the extended keys generated by the key transform function sections and outputting ciphertext, and decrypting input ciphertext and outputting plaintext.

According to still another aspect of the present
10 invention, there is provided an extended key generation method, comprising the steps of: inputting different keys (KC, kcl, ..., kcn-1) in units of rounds;

generating a first key from the inputted key;
transforming the generated first key by using
15 a predetermined substitution table; and

computing an extended key on the basis of the transformed result and a second key obtained from the inputted key.

According to still another aspect of the present
20 invention, there is provided a computer readable storage medium which stores a program for making a computer: generate a first key from different keys (KC, kcl, ..., kcn-1) inputted in units of rounds; transform the generated first key by using
25 a predetermined substitution table; and compute an extended key on the basis of the transformed result and a second key obtained from the inputted key.

09652157 "083100

According to the present invention, in each key transform function section, the first key transforming means executes a transforming process using a predetermined substitution table on the basis
5 of the first key obtained from an input key, and the extended key computing means computes an extended key on the basis of the transformed result of the first key transforming means and a second key obtained from the input key.

10 In this manner, since a simple arrangement without adding any external device is used, and a nonlinear transforming process using a substitution table is done upon generating each extended key, the apparatus price and scale can be suppressed and the randomness of
15 extended keys can be improved while preventing generation of weak keys, thus improving cryptological robustness.

Furthermore, the data randomization part has a plurality of substitution tables for encryption and
20 decryption, and one of the substitution tables of the data randomization part is common to those of the first key transforming means, thus reducing the circuit scale of the apparatus.

According to the present invention, there can
25 be provided an extended key generator, encryption/decryption unit, extended key generation method, and storage medium, which can improve randomness of

09652157.083100

extended keys while suppressing an increase in apparatus price and circuit scale and preventing generation of weak keys, and can improve cryptological robustness.

5 Additional objects and advantages of the invention will be set forth in the description which follows, and in part will be obvious from the description, or may be learned by practice of the invention. The objects and advantages of the invention may be realized and
10 obtained by means of the instrumentalities and combinations particularly pointed out hereinafter.

BRIEF DESCRIPTION OF THE SEVERAL VIEWS OF THE DRAWING

The accompanying drawings, which are incorporated in and constitute a part of the specification, illustrate presently preferred embodiments of the invention,
15 and together with the general description given above and the detailed description of the preferred embodiments given below, serve to explain the principles of the invention.

20 FIGS. 1A and 1B are block diagram for explaining DES as an example of conventional common key cipher;

FIG. 2 is a block diagram showing the arrangement of an encryption/decryption unit according to the first embodiment of the present invention;

25 FIG. 3 is a block diagram showing the arrangement of an extended key generator in the encryption/decryption unit of the first embodiment;

09652157 083100

FIGS. 4A and 4B are views for explaining setup values of constant registers in the first embodiment;

FIG. 5 is a view for explaining the configuration of an S box in the first embodiment;

5 FIG. 6 is a view for explaining setups of a rotate shifter in the first embodiment;

FIG. 7 is a block diagram showing the structure of a round function in the first embodiment;

10 FIG. 8 is a flow chart showing the operation of the encryption/decryption unit;

FIG. 9 is a diagram for explaining the operation in the first embodiment;

15 FIG. 10 is a block diagram showing the arrangement of a key transform function applied to an extended key generator according to the second embodiment of the present invention;

FIG. 11 is a block diagram showing the arrangement of an extended key generator according to the third embodiment of the present invention;

20 FIG. 12 is a view for explaining setups of a substitution part in the third embodiment;

FIG. 13 is a flow chart showing the operations of the embodiment shown in FIG. 11;

25 FIG. 14 is a functional block diagram showing the arrangement of a smart card that embodies the extended key generator, encryption/decryption unit, and storage medium of the present invention;

09652157.083100

FIG. 15 is a diagram for explaining an encryption/decryption unit according to the fourth embodiment of the present invention;

FIG. 16 is a diagram for explaining a modification of the fourth embodiment;

FIG. 17 is a diagram for explaining another modification of the fourth embodiment; and

FIGS. 18A and 18B are diagrams for explaining modifications of the fourth embodiment.

DETAILED DESCRIPTION OF THE INVENTION

The preferred embodiments of the present invention will be described hereinafter with reference to the accompanying drawings.

(First Embodiment)

FIG. 2 is a block diagram showing the arrangement of an encryption/decryption unit according to the first embodiment of the present invention, and FIG. 3 is a block diagram showing the arrangement of an extended key generator in the encryption/decryption unit shown in FIG. 2.

This encryption/decryption unit is implemented as an encryption/decryption processor for a computer such as a personal computer, workstation, or the like, and executes encryption and decryption by hardware or software. More specifically, the encryption/decryption unit comprises an extended key generator 10 for generating n extended keys K_1 to K_n from a common key,

0052157-083100

and a data randomization part 20 for encrypting or
decrypting using the extended keys K_1 to K_n generated
by the extended key generator 10 in order in rounds R_1
to R_n . That is, the extended key generator 10 and data
5 randomization part 20 are commonly used in encryption
and decryption, and when the encryption/decryption unit
is implemented by software, programs indicating their
operations are installed in advance from a storage
medium. Note that a permutation process may be
10 inserted between the extended key generator 10 and data
randomization part 20.

The extended key generator 10 has
cascade-connected key transform functions fk_1 to fk_n
(to be also simply referred to as a key transform
15 function fk hereinafter), which respectively correspond
to the rounds R_1 to R_n . Upon receiving a common key KC
or intermediate key transformed results k_{c1} to k_{cn-1} ,
the key transform functions fk_1 to fk_n output the
extended keys K_1 to K_n obtained by transforming these
20 inputs to round functions fr_1 to fr_n of the data
randomization part 20, and input separately obtained
intermediate key transform functions k_{c1} to k_{cn-1} to
key transform functions fk_2 to fk_n of the next stage.

The key transform functions fk_1 to fk_n
25 respectively comprise temporary key registers 11_1
to 11_n , constant registers 12_1 to 12_n , XOR elements 13_1
to 13_n , S boxes 14_1 to 14_n , extended transformers 15_1

09652157 083100

to 15_n , adders 16_1 to 16_n , and rotate shifters 17_1 to 17_{n-1} , as shown in FIG. 3. Note that a rotate shifter 17_n of the last stage is omitted since there is no key transform function $fk(n+1)$ in the next stage.

5 The temporary key register 11_i (for $1 \leq i \leq n$; the same applies to the following description) holds a common key input to the extended key generator 10 or an intermediate key transformed result input from a key transform function $kf(i-1)$ of the previous stage, and
10 a 56-bit register is used in this embodiment.

 The constant register 12_i is set with a constant in correspondence with the number of rounds to which a key transform function fki belongs, and can supply that constant to the XOR element 13_i . More specifically, as
15 shown in FIG. 4A that exemplifies the number n of rounds = 16, constants to be held in the constant registers 12_i are symmetrically set (former and latter halves have symmetric constants) to have central values
20 ($n = 8, 9$) of the number of rounds as the center, since the constant registers 12_i must also be able to generate extended keys $K1$ to $K16$ in reverse order
25 ($K16$ to $K1$). However, the present invention is not limited to such specific setup, and constants to be held can be arbitrarily set as long as extended keys $K1$ to $K16$ must also be able to generated in reverse order
 ($K16$ to $K1$). For example, as shown in FIG. 4B, constants may be reversed between encryption and

09652157 "083100
007890 2575960

5

10

15

25

(00110110) as its binary expression as output bits.

In this way, input bits (00000001) can be substituted with output bits (00110110).

Note that the substitution table shown in FIG. 5 holds the 0th to 255th elements corresponding to 256 inputs, as described above, and is used to determine a value ranging from 0 to 255 upon receiving a value ranging from 0 to 255.

Also, the S box 14_i is preferably commonly used as some S boxes in the round function f_k to be described later to attain a scale reduction of the apparatus.

The extended transformer 15_i transforms the 8-bit transformed result input from the S box 14_i into a larger value. In this embodiment, the extended transformer 15_i has a function of extending the 8-bit transformed result by shifting it to the left by 4 bits and embedding "0" in lower 4 bits, and inputting the obtained 12-bit extended transformed result to the adder 16_i .

Note that the shift amount of the extended transformer 15_i is preferably equivalently half (= 4 bits) the number of output bits (= 8) of the S box 14_i , since the output bits of the S box 14_i are reflected in two S boxes S_3 and S_4 in the data randomization part 20. Note that the term "equivalently" means that a modification which adds an integer multiple of the number of outputs bits like

00110110 00000001

12 (= 4 + 8 × 1) bit shift or 20 (= 4 + 8 × 2) bit shift
(in other words, a modification that has a shift amount
which makes the remainder equal the number of bits half
(= 4) the divisor) is included in addition to 4-bit
5 shift. When the output bits of the S box 14_i undergo
12-bit shift, they are reflected in S boxes S2 and S3
in place of S boxes S3 and S4; when the output bits
undergo 20-bit shift, they are reflected in S boxes S1
and S2. When the output bits of the S box 14_i are
10 reflected in two S boxes S3 and S4 (including S2 and S3
or S1 and S2), the combination of bits is not limited
to that of 4 bits, but may be combinations of 1 bit
and 7 bits, 2 bits and 6 bits, or 3 bits and 5 bits may
be used in any order. That is, equivalent 1 to 3 and 5
15 to 7 bit shifts may be used in addition to equivalent
4-bit shift.

The adder 16_i has a function of adding (normal
addition with carry-up) the 12-bit extended transformed
result input from the extended transformer 15_i and
20 a second key KB consisting of 32-bit data in the
temporary key register 11_i, and inputting the obtained
sum (32 bits (carried out (bit) is ignored) to the
round function fri of the data randomization part 20 as
an extended key Ki of a round Ri.

25 Note that the first and second keys KA and KB are
individually extracted from continuous areas of the
temporary key register 11_i. However, the present

09652157.083100

invention is not limited to this, and these keys may be extracted from discontinuous areas. That is, the first key KA can be a total of arbitrary 8-bit data in the temporary key register 11_i , and the second key KB can be a total of arbitrary 32-bit data in the temporary key register 11_i . The first and second keys KA and KB may overlap each other. Note that the bit length of the first key KA is preferably equal to the input bit length of the S box of the data randomization part 20 to commonly use the S boxes. The bit length of the second key KB is preferably equal to that of the extended key K_i to simplify design (note that the bit length of the second key KB may be different from that of the extended key K_i , as needed, and in such case, the bit length of the extended key K_i can be finally adjusted by, e.g., contracted or extended permutation).

The rotate shifter 17_i rotates the value of the temporary key register 11_i by a predetermined shift amount, and inputs the rotated value to a temporary key register 11_{i+1} of the next stage. In this embodiment, shift amounts are in units of key transform functions fk_1 to fk_n , as shown in FIG. 6. Note that the shift amount of the rotate shifter 17_i is preferably relatively prime to at least either the number of bits of the common key KC or the number of output bits of the S box 14_i so as to improve randomness of keys, and these three values are most preferably prime to each

09652157-083100

other. The shift amounts are symmetrically set (former and latter halves have symmetric constants) to have a central value ($n = 8$) of the key transform functions fk_1 to $fk_{(n+1)}$ except for the last stage, since
5 extended keys K_1 to K_{16} must also be able to generate extended keys K_1 to K_{16} in reverse order (K_{16} to K_1). However, the present invention is not limited to such specific setup, and the shift amounts and rotation direction of the rotate shifters 17_i can be arbitrarily
10 set as long as extended keys K_1 to K_{16} are also able to generate extended keys K_1 to K_{16} in reverse order (K_{16} to K_1).

On the other hand, the data randomization part 20 has an encryption function of encrypting input
15 plaintext and outputting ciphertext when it receives extended keys K_1 to K_{16} in order from the extended key generator 10 in n rounds from rounds R_1 to R_n . On the other hand, the part 20 has a decryption function of decrypting input ciphertext and outputting plaintext
20 when it receives extended keys K_{16} to K_1 from the extended key generator 10 in an order reverse to that in encryption. The data randomization part 20 has the round functions fr_1 to fr_n which are cascade-connected in order in correspondence with the rounds R_1 to R_{16} .

25 The round function f_{ri} is a function of transforming plaintext or an intermediate encrypted result on the basis of the extended key K_i input

001280"083100 09652157

from the extended key generator 10, and outputting
an intermediate encrypted result or ciphertext in
encryption, and is also a function of transforming
ciphertext or an intermediate decrypted result on the
5 basis of the extended key $K(n+1-i)$ input in reverse
order from the extended key generator 10, and
outputting an intermediate decrypted result or
plaintext in decryption process. In this embodiment,
for example, the round function f_{ri} uses the Feistel
10 structure shown in FIG. 7.

The Feistel structure shown in FIG. 7 comprises
the following arrangement. That is, of input data
blocks made up of two subblocks L_i and R_i , one subblock
 R_i is nonlinearly transformed using an F function on
15 the basis of the extended key K_i , the XOR of this
transformed result and the other subblock L_i is
computed by an XOR element 21, and the computation
result R_{i+1} and one subblock L_{i+1} ($= R_i$) are supplied
to the next stage while interchanging their positions.

Note that the F function in FIG. 7 comprises
20 an XOR element 22 that XORs the extended key K and
subblock R_i (or L_i), and four S boxes S_1 to S_4 for
segmenting the output from the XOR element 22 into four
elements, and respectively nonlinearly transforming
25 these elements. Note that the S boxes S_1 to S_4 have
a substitution table shown in, e.g., FIG. 5, and the
respective S boxes may have a common substitution table

09652157-083100

but may have different ones.

Note that transformation done by each round function fr has a nature called involution, i.e., that original data is restored when identical transformation repeats itself twice. For this reason, when ciphertext is generated by transforming plaintext in the order of extended keys $K1$ to $K16$, the data randomization part 20 can generate plaintext by re-transforming this ciphertext in the order of extended keys $K16$ to $K1$.

The operation of the encryption/decryption unit with the aforementioned arrangement will be explained below also with reference to the flow chart shown in FIG. 8.

Upon encryption, as shown in FIG. 2, an input common key KC or intermediate key transformed result kci is transformed into an extended key Ki in each round using the key transform function fki .

More specifically, as shown in FIG. 9, in the key transform function fki , the XOR element 13_i XORs the 8-bit first key KA extracted from the temporary key register 11_i , and a constant in the constant register 12_i (step $S1$ in FIG. 8), and the S box 14_i linearly transforms this XOR (step $S3$ in FIG. 8). As nonlinear transformation, the input and output are substituted in units of bits to have the relationship shown in, e.g., FIG. 5. This substitution result is left-shifted by 4 bits (= 16 times) by the extended transformer 15_i to

09652157-083100

obtain 12 bits of data. Furthermore, the substitution result is expanded to 32 bits by adding 20 bits of leading "0." The 32-bit substitution result is then input to the adder 16_i (step S5 in FIG. 8).

5 The adder 16_i adds the input shift result (32 bits) and the 32-bit second key KB extracted from the temporary key register 11_i, and outputs the sum as the 32-bit extended key Ki to the data randomization part 20 (step S7 in FIG. 8).

10 In this extended key Ki, the 8-bit first key KA transformed by the S box 14_i is located at the 5th to 12th bits from the right (least significant bit). These bit positions correspond to an input to the third and fourth S boxes S3 and S4. Hence, the randomization effect of the S box 14_i in the extended key generator
15 10 can be reflected in the two S boxes S3 and S4 in the data randomization part 20, thus improving randomness of the extended key.

20 In the data randomization part 20, plaintext is transformed based on extended keys K1 to Kn in units of round functions fr1 to frn, and is finally transformed into ciphertext via intermediate encrypted results.

25 On the other hand, upon decryption, the extended key generator 10 executes key transform processes in reverse order to that in encryption upon receiving the common key KC as in the aforementioned case, and sequentially outputs extended key Kn to K1 to the data

001530" 45722960

keys input to the respective rounds can become easily and reliably different from each other.

Furthermore, assuming that the shift amount of the rotate shifter 17_i is relatively prime to, e.g., the
5 number of output bits of the S box 14_i , nearly all first keys KA in the rounds $R1$ to Rn can be different from each other, and the aforementioned effect can be obtained more easily and reliably.

09652157-083100
Furthermore, in each key transform function fki ,
10 since the extended transformer 15_i extends and transforms the transformed result of the S box 14_i , and inputs the result to the adder 16_i , the randomization effect of the first key KA can be reflected in an arbitrary area of the extended key Ki in addition to
15 the aforementioned effects.

Since extended transformation of the extended transformer 15_i is implemented by shifting the predetermined number of bits, the aforementioned effects can be easily and reliably obtained.

20 Furthermore, since the data randomization part 20 has a plurality of S boxes $S1$ to $S4$ for encryption and decryption, and some S boxes of the data randomization part 20 are common to the S boxes 14_i of the key transform functions $fk1$ to fkn , the device scale can be
25 reduced.

In each of the key transform function $fk1$ to fkn , since the extended transformer 15_i shifts to the left

the transformed result received from the S box 14_i by the number of bits half that of the transformed result or the number of bits obtained by an integer multiple of the number of bits of the transformed result to the half number of bits, and inputs the shift result to the adder 16_i , the randomization effect of the first key K_A can be reflected in an area left-shifted by the extended key K_i . In this case, since the randomization effect of the first key K_A can be reflected in an area input to the S boxes S_3 and S_4 of the data randomization part 20, cryptological robustness can be further improved.

(Second Embodiment)

FIG. 10 is a block diagram showing the arrangement of a key transform function applied to an extended key generator according to the second embodiment of the present invention. The same reference numerals in FIG. 10 denote the same parts as those in FIG. 3, a detailed description thereof will be omitted, and only differences will be explained below. Note that a repetitive description will also be avoided in the embodiments to be described later.

That is, this embodiment is a modification of the first embodiment, and aims at further improving randomness of extended keys. More specifically, in each key transfer function, the aforementioned transform elements including the constant registers

09652157.083100

12_i, XOR elements 13_i, S boxes 14_i, and extended transformers 15_i are parallelly connected between the temporary key register 11_i and adder 16_i, as shown in FIG. 10.

5 The two S boxes 14_i may be of either one type or a plurality of types. When a plurality of types of S boxes are used, those types are preferably set so that the former group of key transform functions fk1 to fk8, and the latter group of key transform functions fk9 to
10 fk16 become vertically symmetrical from the central values (fk8 and fk9), since extended keys K_i must be able to be generated in both normal and reverse orders on the basis of the common key KC.

 The two extended transformers 15_i may have
15 identical shift amounts. Since the randomization effect of the two S boxes 14_i must be reflected over a broader range, the outputs from the S boxes 14_i are preferably shifted to the left using different shift amounts. In this case, if one extended transformer 15_i
20 is set to implement 4-bit left shift, and the other extended transformer 15_i is set to implement 20-bit left shift, the randomization effect of the first key KA can be conveniently reflected in all the S boxes S1 to S4 of the data randomization part 20.

25 With the aforementioned arrangement, since randomness using the first key KA can be further improved, the randomness of extended keys K_i can be

09652157 "083100

(Third Embodiment)

This embodiment is a modification of the first or second embodiment, and comprises, in place of the temporary shift register 11_i and rotate shifter 17_i , a substitution part 18_i which nonlinearly substitutes respective bits of an input common key KC or one of intermediate keys k_{c1} to k_{cn-1} , inputs some bits of the obtained intermediate key to the XOR element 13_i and adder 16_i of the own stage, and also inputs the whole intermediate key to a substitution part $18_{(i+1)}$ of the next stage. Note that the substitution part 18_i does not substitute respective bits of the input common key KC.

The respective substitution parts 18_i are set so that the result after n substitutions of the common key KC in normal order becomes equal to the original common key KC, since they must be able to generate extended keys K_i on the basis of the common key KC in both normal and reverse orders. Also, transformation is done in ascending order upon encryption, and inverse transformation is done in descending order upon decryption, as shown in FIG. 12 that exemplifies

5 In the embodiment shown in FIG. 11, each substitution part 18_i executes a process for nonlinearly transforming the common key KC in step S21 in FIG. 13. In step S23, the XOR element 13_i XORs a first key KA obtained from the substitution part 18_i and a constant held in the constant register 12_i. In step S25, the S box 14_i nonlinearly transforms the XOR output from the XOR element 13_i using a substitution table. In step S27, the extended transformer 15_i shifts the nonlinearly transformed value to the left by 4 bits, thus obtaining a 12-bit extended transformed result. Furthermore, the 12-bit transformed result is expanded to 32 bits by adding 20 bits of leading "0." In step S29, the 32-bit extended transformed result is added to a second key KB obtained from the substitution part 18_i to generate an extended key.

25

In the above embodiments, the XOR element 13; for

5
10

15

20

25

(Fourth Embodiment)

An encryption/decryption unit according to the fourth embodiment of the present invention will be described below using FIG. 15. This encryption/decryption unit 30 has an arrangement described in one of the first to third embodiments, and is used to protect digital information such as image data, music data, and the like (to be referred to as raw data hereinafter).

Assume that the encryption/decryption unit 30 is implemented on a personal computer PC by installing a program from a storage medium, as shown in FIG. 15. The encryption/decryption unit 30 encrypts raw data input to the personal computer PC using, e.g., a user ID as a common key, and stores the obtained encrypted data (corresponding to the aforementioned ciphertext) in a portable memory element 31. As such memory element 31, a smart card, smart media, memory card, or the like may be used.

The memory element 31 is distributed to the user's home, and an encryption/decryption unit (not shown) in the user's home decrypts the encrypted data in the memory element 13 on the basis of the self user ID and reproduces obtained image data or music data from, e.g., a loudspeaker or the like. In this manner, raw data (contents) can be distributed to only users who have made a subscription contract in advance.

09652157-083100

Various modifications of this embodiment are available as follows. For example, as shown in FIG. 16, a recording unit 32 comprising the encryption/decryption unit 30 as a hardware circuit may be provided in place of the personal computer PC. With this arrangement, upon writing contents in the memory element 31, the encryption/decryption unit 30 encrypts raw data based on, e.g., a user ID, and stores encrypted data in the memory element 31. The processes from delivery to the home to decryption are the same as those described above. In this manner, the encryption/decryption unit 30 may be provided to the dedicated recording unit 32 in place of a versatile computer such as the personal computer PC and the like.

Also, as shown in FIG. 17, a host computer 33 with the encryption/decryption unit 30 may be connected to the personal computer PC via a network NW. In this case, encrypted data downloaded from the host computer 33 is stored in the memory element 32 via the personal computer PC in the encrypted state. The processes from delivery to the home to decryption are the same as those described above. According to this modification, in addition to the aforementioned effect, contents (raw data) on the network NW can be prevented from eavesdropped.

Furthermore, as shown in FIGS. 18A and 18B, a DVD (digital versatile disc) may be used as the memory

09652157 "083100

element. In the case shown in FIG. 18A, a DVD 34 that pre-stores encrypted data is distributed to the user. The encryption/decryption unit 30 at the user's home decrypts the encrypted data in the DVD 34, and
5 reproduces obtained image data or music data from a loudspeaker or the like.

Also, in the case shown in FIG. 18B, raw data such as image data, music data, or the like is encrypted by the encryption/decryption unit 30 at the user's home
10 using a predetermined common key, and the obtained encrypted data is stored in a DVD-RAM 35.

This encrypted data is decrypted by the predetermined common key set by the user, but cannot be decrypted by a third party unless the common key is
15 disclosed. Therefore, personal image data and music data can be saved while being protected from third parties.

(Other Embodiments)

As a storage medium that stores a program for
20 implementing the processes of the extended key generator and encryption/decryption unit of the present invention, a magnetic disk, floppy disk, hard disk, optical disk (CD-ROM, CD-R, DVD, or the like), magneto-optical disk (MO or the like), semiconductor
25 memory, and the like may be used. In practice, the storage format is not particularly limited as long as a storage medium can store the program and can be

001590" 25725960

read by a computer.

5 An OS (operating system) which is running on
a computer or MW (middleware) such as database
management software, network software, or the like may
execute some of processes that implement the above
embodiment, on the basis of an instruction of the
program installed from the storage medium in the
computer.

10 Furthermore, the storage medium in the present
invention is not limited to a medium independent from
the computer, but includes a storage medium which
stores or temporarily stores a program downloaded from
a LAN, the Internet, or the like.

15 The number of storage media is not limited to one,
and the storage medium of the present invention
includes a case wherein the processes of the above
embodiment are implemented from a plurality of media,
and either medium arrangement may be used.

20 Note that the computer in the present invention
executes processes of the above embodiment on the basis
of programs stored in the storage medium, and can be
either an apparatus consisting of a single device such
as a personal computer, or a system built by connecting
a plurality of devices via a network.

25 The computer in the present invention is not
limited to a personal computer, and includes
an arithmetic processing device, microcomputer, and the

09552157 "0831.00

like included in an information processing apparatus, i.e., includes all devices and apparatuses that can implement the functions of the present invention via programs.

5 The present invention is not limited to a DES cryptosystem but can be applied to any other block cryptosystems using round functions. For example, the present invention may be applied to cryptosystems such as Lucifer, LOKI, MISTY1, MISTY2, and SAFER (Secure and
10 Fast Encryption Routine), and the like.

 In the above embodiments, the S box makes nonlinear transformation using a substitution table. Alternatively, the S box may make nonlinear transformation using a wiring pattern.

15 In the embodiment shown in FIG. 10, two sets of transform elements including the constant registers 12_i , XOR elements 13_i , S boxes 14_i , and extended transformers 15_i are parallelly arranged. Alternatively, three or more sets of transform
20 elements may be parallelly arranged.

 Various other modifications of the present invention may be made within the scope of the invention.

 Additional advantages and modifications will
25 readily occur to those skilled in the art. Therefore, the invention in its broader aspects is not limited to the specific details and representative embodiments

09652157 "083100

shown and described herein. Accordingly, various modifications may be made without departing from the spirit or scope of the general inventive concept as defined by the appended claims and their equivalents.

09652157-083100